

# PSWR-E4

2-channel IR-receiver

**System:**

Butterfly



**Characteristics:**  
 PSWR-E4 can be used to control windows, electric shutter or a window share. Command by infrared signal or front panel buttons.

**Note:**  
 Jumper J3 selects the PSWR unit input voltage 12 or 24V. Jumpers for connectors J4 and J5 have to be connected between pins 1 and 2 when programming the receiver. When jumpers are connected to pins 2 and 3, the receiver cannot be programmed. Then also the buttons of the receiver

**Technical specification:**

Enclosure: ABS  
 Dimensions: 84 x 84 x 36 mm  
 Weight: 90 g  
 Supply voltage: selectable 12/24 Vdc according to windows opener motor

Output: 1 motor output  
 Max load: 2 A  
 Connectors: Screw connectors for motor output and operating voltage  
 Connectors for external PSAE IR-eye: No  
 Adaptivity feature: No  
 Operating temperature: -20 – +40 °C  
 CE

